

# AVS-1200S

## Multimedia Switcher



The ABtUS **AVS-1200S** is a high performance Multimedia Switcher designed for any small medium multimedia classroom or boardroom application.

AVS-1200S can also be configured together with the AVS-1200C as the Multimedia Controller Switcher.

### Features

- RS-232 Controllable
- Easy Installation with standard AV I/O connector and cabling
- Fully self contained / integrated AV switcher
- Supports 3 VGA input with resolutions from VGA to SXGA
- Works well with any monitors and projectors

### Technical specification

<b>Input:</b>	VGA Input x 3 (*D-Sub 15pin)
	PC-Audio x 3 (*3.5mm mini jack)
	C-Video x 1 (*1xRCA)
	Stereo Audio x 1 (*2xRCA)
	Microphone x 1 (*3.5mm)
	Microphone x 1 (*6.3mm)
<b>Output:</b>	VGA output x 2 (*900MHz)
	**1 to projector and 1 for monitor
	C-Video x 1 (*1xRCA)
	Main Stereo Audio x 1 (*2xRCA)
<b>Configurable com port:</b>	3-in 2-out VGA Distribution Amplifier Switcher (900MHz R+G+B)
<b>Max resolution:</b>	1280 x 1024
<b>All cable length:</b>	Up to 28 meter
<b>Control:</b>	RS-232 controllable (8 Data Bit and 1 Stop Bit)
<b>Baud rate:</b>	9600
<b>Parity bit</b>	Non
<b>LED indicator:</b>	With LED for power indication and confirmation
<b>Video selection:</b>	All Video/VGA Input Switching      Digital
<b>Audio selection:</b>	Audio Input Switching                      Digital
<b>Volume:</b>	Main Volume Control                        Digital
<b>Mic gain:</b>	Microphone Input Gain Control          Default
<b>User configurable:</b>	Yes
<b>Housing:</b>	Metal
<b>Dimension:</b>	235 x 125 x 30 mm
<b>Weight:</b>	400g

# AVS-1200S

## Multimedia Switcher

### Typical applications

The AVS-1200S is part of the ABtUS series of high quality, high bandwidth and cost effective Distribution Amplifiers and Switchers especially for professional installers. ABtUS products can be found in industrial, commercial, educational, military and government applications such as:

- Schools / Classrooms
- Training rooms
- Workstation environments
- Multipurpose Halls

### Diagram

